



SIMATIC ET 200SP, Analog input module, AI Energy Meter 480V AC ST, suitable for BU type D0, channel diagnostics

General information	
Product type designation	AI Energy Meter 480VAC ST
Firmware version	
<ul style="list-style-type: none"> FW update possible 	Yes
usable BaseUnits	BU type D0
Supported power supply systems	TT, TN
Product function	
<ul style="list-style-type: none"> Voltage measurement — without voltage transformer — with voltage transformer Current measurement — without current transformer — with current transformer — With Rogowski coil — With current-voltage-converter Energy measurement Frequency measurement Power measurement Active power measurement Reactive power measurement Power factor measurement Active factor measurement Reactive power compensation Line analysis I&M data Isochronous mode 	Yes Yes Yes Yes No Yes No No Yes Yes Yes Yes Yes Yes Yes No No No Yes; I&M0 to I&M3 No
Engineering with	
<ul style="list-style-type: none"> STEP 7 TIA Portal configurable/integrated from version STEP 7 configurable/integrated from version PROFIBUS from GSD version/GSD revision PROFINET from GSD version/GSD revision 	V13 SP1 V5.5 SP4 and higher GSD Revision 5 V2.3
Operating mode	
<ul style="list-style-type: none"> Cyclic measured value access Acyclic measured value access Fixed measured value sets Freely definable measured value sets 	Yes Yes Yes Yes
CiR - Configuration in RUN	

Reparameterization possible in RUN	Yes
Calibration possible in RUN	Yes
Installation type/mounting	
Mounting position	any
Supply voltage	
Design of the power supply	Supply via voltage measurement channel L1
Type of supply voltage	AC 100 - 277 V
permissible range, lower limit (AC)	90 V
permissible range, upper limit (AC)	293 V
Line frequency	
<ul style="list-style-type: none"> permissible range, lower limit permissible range, upper limit 	47 Hz 63 Hz
Power loss	
Power loss, typ.	0.6 W
Address area	
Address space per module	
<ul style="list-style-type: none"> Inputs Outputs 	256 byte 12 byte
Hardware configuration	
Automatic encoding	Yes
<ul style="list-style-type: none"> Mechanical coding element 	Yes
Selection of BaseUnit for connection variants	
<ul style="list-style-type: none"> 2-wire connection 	BU type D0, BU20-P12+A0+0B
Time of day	
Operating hours counter	
<ul style="list-style-type: none"> present 	Yes
Analog inputs	
Cycle time (all channels), typ.	50 ms; Time for consistent update of all measured and calculated values (cyclic und acyclic data)
Cable length	
<ul style="list-style-type: none"> unshielded, max. 	200 m
Analog value generation for the inputs	
Measurement principle	Sigma Delta
Sampling frequency, max.	1 024 kHz
Interrupts/diagnostics/status information	
Alarms	
<ul style="list-style-type: none"> Diagnostic alarm Limit value alarm Hardware interrupt 	Yes Yes Yes; Monitoring of up to 16 freely selectable process values (exceeding or undershooting of value)
Diagnostics indication LED	
<ul style="list-style-type: none"> Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics 	Yes Yes; green LED Yes; red Fn LED Yes; green/red DIAG LED
Integrated Functions	
Measuring functions	
<ul style="list-style-type: none"> Measuring procedure for voltage measurement Measuring procedure for current measurement Type of measured value acquisition Curve shape of voltage Buffering of measured variables Parameter length Bandwidth of measured value acquisition 	TRMS TRMS seamless Sinusoidal or distorted Yes 74 byte 2 kHz
Measuring range	
<ul style="list-style-type: none"> Frequency measurement, min. Frequency measurement, max. 	45 Hz 65 Hz

Measuring inputs for voltage	
— Measurable line voltage between phase and neutral conductor	277 V
— Measurable line voltage between the line conductors	480 V
— Measurable line voltage between phase and neutral conductor, min.	90 V
— Measurable line voltage between phase and neutral conductor, max.	293 V
— Measurable line voltage between the line conductors, min.	155 V
— Measurable line voltage between the line conductors, max.	508 V
— Internal resistance line conductor and neutral conductor	3.4 MΩ
— Power consumption per phase	20 mW
— Impulse voltage resistance 1,2/50μs	1 kV
— Measurement category for voltage measurement in accordance with IEC 61010-2-030	CAT II; CAT III in case of guaranteed protection level of 1.5 kV
Measuring inputs for current	
— measurable relative current (AC), min.	1 %; Relative to the secondary rated current 5 A
— measurable relative current (AC), max.	100 %; Relative to the secondary rated current 5 A
— Continuous current with AC, maximum permissible	5 A
— Apparent power consumption per phase for measuring range 5 A	0.6 V·A
— Rated value short-time withstand current restricted to 1 s	100 A
— Input resistance measuring range 0 to 5 A	25 mΩ
— Surge strength	10 A; for 1 minute
— Zero point suppression	Parameterizable: 2 ... 250 mA, default 50 mA
Accuracy class according to IEC 61557-12	
— Measured variable apparent power	0.5
— Measured variable active power	0.5
— Measured variable power factor	0.5
— Measured variable active energy	0.5
— Measured variable neutral current	0.5; calculated
— Measured variable phase angle	±1 °; not covered by IEC 61557-12
— Measured variable frequency	0.05
Potential separation	
Potential separation channels	
• between the channels	No
• between the channels and backplane bus	Yes; 3 700V AC (type test) CAT III
Isolation	
Isolation tested with	2 300V AC for 1 min. (type test)
Ambient conditions	
Ambient temperature during operation	
• horizontal installation, min.	0 °C
• horizontal installation, max.	60 °C
• vertical installation, min.	0 °C
• vertical installation, max.	50 °C
Altitude during operation relating to sea level	
• Ambient air temperature-barometric pressure-altitude	On request: Ambient temperatures lower than 0 °C (without condensation) and/or installation altitudes greater than 2 000 m
Dimensions	
Width	20 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	45 g

Other

Data for selecting a voltage transformer

- Secondary side, max. 296 V

Data for selecting a current transformer

- Burden power current transformer x/1A, min. As a function of cable length and cross section, see device manual
- Burden power current transformer x/5A, min. As a function of cable length and cross section, see device manual

last modified:

1/16/2021 