# OMRON

# **Programmable Terminal**

# **NB** Series



- Appealing to see
- Enjoyable to use

# The future-proof, compact HMI

Give more value to your machines with Omron's NB Series: compact range application HMI.

Enjoy his the aesthetic sense and excellent visibility.

Our expertise in Factory automation give you warranty of quality and a total freedom to build up optimal applications.

Newly added remote control features help to reduce the time and work involved in maintenance.

#### Enjoyable to use

#### **Global support from local site**

- Flexible remote access function NEW
- Powerful remote operation NEW
- On/off-line simulation
- USB memory stick support



#### Easily create intuitive operator screens

- Flexible window handling
- Easy animation
- Extensive language support
- Powerful macros







MADE

# 



#### **Pleasant to program**

#### Ready to use functions for your machine

- Always informed about alarms
- Easy data presentation
- Multiple security options

#### The perfect partner for Omron devices

- Serial and Ethernet connectivity
- Connection to Omron and non-Omron devices

#### Appealing to see in a wide product range

- Screen size from 3.5 to 10.1 inch
- LED backlighted TFT LCD
- Wide viewing angle
- More than 65,000 display colors
- High brilliance




# Enjoyable to use

The newly added remote control features significantly save you time, and the flexible design features make screen creation easier. All these features greatly contribute to your global scale business.

#### **Global support from local site**

#### Flexible remote access function NEW

Besides conventional web browsers, now NB Series supports faster and secure Virtual network computing (VNC), providing flexible remote access.



#### Web browser

Support OSSupport web browserWindowsInternet Explorer 8/9, Google Chrome 32.0., Firefox 27.0iOS 6Safari

Monitoring and operating screens via various PC web browsers.

#### VNC Server - BYOD (Bring Your Own Device)

The VNC client application "HMI Remote Viewer", which is already used for NA Series, can also be used for NB Series.






Search by "HMI Remote Viewer' for free download.

## Powerful remote operation NEW

With the newly added features such as FTP Server and CSV data-copying features, you can change machine parameters from remote locations or host PC, and collect production data. Now graphics can be updated even during the operation, and visual can be changed without stopping the HMI following changes in machines and recipes.



#### Easily create intuitive operator screens

#### Flexible window handling

NB Series easily creates screens for your project. Besides the standard window, you can also create 'window-in window'. Furthermore, it also supports bottom windows and transparency for pop-up windows.

#### **Easy animation**

Animations can be created easily. For example, you can show a different status with text and graphics, or move the components while changing them. This easy animation feature makes the operation easier to understand and eliminates the need for expertise.


#### **Extensive language support**

Thanks to the supported 32 languages and Text Library function, you will find it easy to manage texts in multi-language. This allows users to operate the HMI in the language they choose.


#### **Powerful macros**

Thanks to its powerful macros, you can perform calculations and comparisons or iterations, and mathematical functions. It also enables you to do even more.

Pop-up & Customizable Windows More Screen Space Flexible Designs Prompts & Notifications Text input: TEXT HOME Number input: BASIC GRAPHIC 1 2 3 CLI DVANCE 4 6 <-5 7 8 9 APP. ENTER 0







# Pleasant to program

#### Ready to use functions for your machine

The feature-rich NB series has everything you will need for creating applications for a wide range machines and in many industries, for example, packaging, food, plastics and textiles. From a simple lid placing or loading/unloading machine right up to an in-line filling or sealing /labeling packaging machine. Download free of charge NB-Designer software from Omron web site.



#### Always informed about alarms

Event monitoring (alarming) is both flexible and easy to use. Not only do you have the possibility to enter bit and word alarms for on/off or on-condition triggering, there is also the possibility to use different fonts and color to indicate varying degrees of status and priorities. Specific alarms are indicated with an audible buzzer sound, as well as by an accompanying text message, and you can even create pop-up alarms for situations where immediate action has to be taken.



#### **Easy data presentation**

Graphical representation of real-time and historical data is easy with the NB series. As well as display of time sampling and trending data, you have the option to save sampling data (max. 16 consecutive words) of basic real-time trending data. And you can plot using x/y coordinates, in which case sampling can be done via single or multiple points and with historical data. Furthermore, data can be presented in a variety of ways, such as sampling points using x and y components.



#### **Multiple security options**

Protecting your developed project with a password using the NB series is both a simple and secure matter. Among the comprehensive security options is the possibility to define up to 16 minimum security levels on screens, buttons and inputs, and you can set up to 32 specific permission controls for each operator. There is also a register condition (bit/word) control for a check of actual condition against a predefined value, and a standard operator confirmation check to confirm that critical actions have been performed by the operator.

#### The perfect partner for Omron devices

Omron Compact controllers perfectly match your specific automation requirement and connection to the NB series is possible via Serial or Ethernet.

Ethernet protocols, FTP or VNC make easy remote access for maintenance or data gathering and allows digitalisation of your machine.




# Programmable Terminals **NB Series**

# The feature-rich, economic programmable terminal

- More than 65,000 display colors TFT, color touch-screen for all models
- Available in sizes ranging from 3 to 10 inches
- Long-life LED backlight
- Serial, USB or Ethernet communication
- USB memory stick support



## **System Configuration**



Controller

Windows is registered trademarks of Microsoft Corporation in the USA and other countries.

Microsoft product screen shot(s) reprinted with permission from Microsoft Corporation.

Apple and Apple logo are registered trademarks of Apple Inc. in the USA and other countries. App Store is a service mark of Apple Inc. Google Play and the Google Play logo are trademarks of Google LLC.

Safari is trademark of Apple Inc., registered in the U.S. and other countries.

Other company names and product names in this document are the trademarks or registered trademarks of their respective companies. The product photographs and figures that are used in this catalog may vary somewhat from the actual products.

8

# **Ordering Information**

#### **Programmable Terminals**

Product name	Specifications	Model
NB3Q	3.5 inch, TFT LCD, Color, $320 \times 240$ dots	NB3Q-TW00B
	3.5 inch, TFT LCD, Color, $320 \times 240$ dots, USB Host, Ethernet	NB3Q-TW01B
NB5Q	5.6 inch, TFT LCD, Color, 320 × 234 dots	NB5Q-TW00B
	5.6 inch, TFT LCD, Color, $320 \times 234$ dots, USB Host, Ethernet	NB5Q-TW01B
NB7W	7 inch, TFT LCD, Color, 800 × 480 dots	NB7W-TW00B
	7 inch, TFT LCD, Color, $800 \times 480$ dots , USB Host, Ethernet	NB7W-TW01B
NB10W	10.1 inch, TFT LCD, Color, 800 × 480 dots , USB Host, Ethernet	NB10W-TW01B

#### Options

Product name	Specifications	Model
Software	Supported Operating Systems: Windows 10, Windows 8.1, Windows 8, Windows 7, Windows Vista <sup>®</sup> , Windows XP (SP3 or higher). Note: Except for Windows XP 64-bit version Download from Omron's regional websites.	NB-Designer *
NB-to-PLC Connecting cable	For NB to PLC via RS-232C (CP/CJ/CS), 2 m	XW2Z-200T
	For NB to PLC via RS-232C (CP/CJ/CS), 5 m	XW2Z-500T
Cabic	For NB to PLC via RS-422A/485, 2 m	NB-RSEXT-2M
	For the NB3Q contains 5 sheets	NB3Q-KBA04
Disular anatastica shaata	For the NB5Q contains 5 sheets	NB5Q-KBA04
Display protective sheets	For the NB7W contains 5 sheets	NB7W-KBA04
	For the NB10W contains 5 sheets	NB10W-KBA04
Attachment	Mounting bracket for NT31/NT31C series to NB5Q series	NB5Q-ATT01

Note: Use a standard USB cable (Type A male to Type B male) or standard Ethernet cable (10 BASE-T/100 BASE-TX twisted-pair cable) to connect the NB series to software (personal computer). Use a standard Ethernet cable (10 BASE-T/100 BASE-TX twisted-pair cable) to connect the NB series to a PLC. For detail, refer to the NB

Series Setup Manual (Cat. No. V107).

\* The NB5Q-TW01B and NB7W-TW01B are supported by NB-Designer version 1.10 or higher.

\* The NB3Q-TW0 B and NB10W-TW01B are supported by NB-Designer version 1.20 or higher.

#### **System Configuration**

Items	Minimum Configurations
Operating System (OS)	Microsoft Windows XP (SP3 or higher) Microsoft Windows Vista (32-bit or 64-bit edition) Microsoft Windows 7 (32-bit or 64-bit edition) Microsoft Windows 8 (32-bit or 64-bit edition) Microsoft Windows 8.1 (32-bit or 64-bit edition) Microsoft Windows 10 (32-bit or 64-bit edition)
CPU	Windows computers with CPU recommended for OS
Memory	512 MB or more
Hard Disk	2.5 GB or more, with the disk space more than 800 MB at least
Display	Supports the display with resolution of $800 \times 600$ and 16-bit high color (1024 $\times$ 768 and 32-bit true color are recommended.).
Communication ports	RS-232C Port, USB Port, Ethernet Port

#### **Recommended USB Memory**

Product name	Specifications	Model
USB memory stick	Capacity: 2 GB	FZ-MEM2G
	Capacity: 8 GB	FZ-MEM8G

## **NB Series**

# Specifications

#### HMI

Specifications	NB	3Q	NB	5Q	NB7W		NB10W
Specifications	TW00B	TW01B	TW00B	TW01B	TW00B	TW01B	TW01B
Display type	3.5" TI	T LCD	5.6" TI	T LCD	7" TF	T LCD	10.1" TFT LCD
Display resolution (H $\times$ V)	320 × 240		320 × 234		800 × 480 800 × 480		
Number of colors		65,536					
Backlight	LED						
Backlight lifetime	50,000 hours of operating time at the normal temperature (25°C)*						
Touch panel	Analog resistive membrane type, resolution $1024 \times 1024$ , life: 1 million touch operations						operations
Dimensions in mm (H $\times$ W $\times$ D)	$103.8 \times 129.8 \times 52.8$ $142 \times 184 \times 46$ $148 \times 202 \times 46$					210.8 × 268.8 × 54.0	
Weight	300 g max.	305 g max.	620 g max.	627 g max.	710 g max.	715 g max.	1525 g max.

\* This is the estimated time when the luminous intensity is decreased by 50% per LED at room temperature and humidity. It is a typical value.

#### Functionality

Specifications	NE	33Q	NB5Q		NB7W		NB10W	
Specifications	TW00B	TW01B	TW00B	TW01B	TW00B	TW01B	TW01B	
Internal memory			128 N	IB (including sy	stem area)			
Memory interface		USB Memory		USB Memory		USB Memory	USB Memory	
Serial (COM1)	(not is) Transmissi 15 m Max. 500 m Max. (F	/422A/485 olated), on distance: (RS-232C), RS-422A/485), D-Sub 9-pin	RS-232C, Transmission distance: 15 m Max., Connector: D-Sub 9-pin					
Serial (COM2)	-	RS-232C/422A/485 (not isolated), Transmission distance: 15 m Max. (RS-232C), 500 m Max. (RS-422A/4 Connector: D-Sub 9-pin				<i>, , , , , , , , , ,</i>		
USB Host		Equivalent to USB 2.0 full speed, type A, Output power 5 V, 150 mA						
USB Slave		Equivalent to USB 2.0 full speed, type B, Transmission distance: 5 m						
Printer connection		PictBridge support						
Ethernet		10/100 base-T	10/100 base-T 10/100 base-T 10/100 bas				10/100 base-T	

#### General

Specifications	NB	NB3Q		NB5Q		NB7W	
	TW00B	TW01B	TW00B	TW01B	TW00B	TW01B	TW01B
Line voltage			20.4 to 27	7.6 VDC (24 VE	DC -15 to 15%)		
Power consumption	5 W	9 W	6 W	10 W	7 W	11 W	14 W
Battery lifetime	5 years (at 25°C) <b>*</b>						
Enclosure rating (front side)	Front operation part: IP65 (Dust proof and drip proof only from the front of the panel)						
Obtained standards	EC Directives, KC, cUL508						
Operating environment	No corrosive gases.						
Noise immunity	Compliant with IEC61000-4-4, 2 KV (Power cable)						
Ambient operating temperature	0 to 50°C						
Ambient operating humidity	10% to 90% RH (without condensation)						

**Note:** Flash memory can be written to up 100,000 times. \* OMRON accepts NB unit including the display device for repair and analysis within five years of the manufacture date.

# **NB Series**

129 153.6

44(min.)

53(max.)

Clamp


D

adlaaaaaaaalli


- 46 -

#### (Units: mm)

## Dimensions




NB7W



Model	Panel cutout (H × V mm)
NB3Q	119.0 (+0.5/–0) × 93.0 (+0.5/–0)
NB5Q	172.4 (+0.5/-0) × 131.0 (+0.5/-0)
NB7W	191.0 (+0.5/-0) × 137.0 (+0.5/-0)
NB10W	258.0 (+0.5/-0) × 200.0 (+0.5/-0)


#### NB5Q Panel 130.8 142 15.5 134 184 6.2 172.2 ..... 飴 fi fi ղլ 170.4 -195 NB10W



Applicable panel thickness: 1.6 to 4.8 mm

## **Related Manuals**

Cat. No	Model	Name
V106	NB-Designer	NB Series NB-Designer Operation Manual
V107	NB3Q, NB5Q, NB7W, NB10W	NB Series Setup Manual
V108	NB3Q, NB5Q, NB7W, NB10W	NB Series Host Connection Manual
V109	NB3Q, NB5Q, NB7W, NB10W	NB Series Startup Guide



Company	Series	Model			
Company	Series	Ethernet communication	Serial communication		
	CP Series	CP1L-EL/-EM, CP2E-N (Built-in Ethernet port) CP1H-X/-XA/-Y, CP1L-L/-M, CP1E-N/-N□□S/-NA (Option Board required)	CP1E-N/-N S/-NA, CP2E-S/-E (Built-in serial port) CP1L-EL/-EM/-L/-M, CP1H-X/-XA/-Y, CP2E-N (Option Board required)		
OMRON	CJ/CJ2/CS/NJ/NX1/NX1P Series	CJ1W-ETN21/EIP21 CS1W-ETN21/EIP21 CJ2HEIP, CJ2M-CPU3_ NJ_01 NX102 NX1P2	CJ1, CJ2, CS1 NJ=01 (Serial communication unit required) NX1P2-==== (Option Board required)		
	C Series		C200HX/HG/HE(-Z) CQM1H CPM1□/2□		
	G9SP Series		G9SP-N C (CP1W-CIF01 Option Board required)		
	For connectable OMRON PLC m Manual (Cat. No. V106).	odels, refer to the Appendices in the			
	FX Series (Port built into CPU)		FX1N/1NC/2N/2NC/3G/3GC FX1S FX3U/3UC/3S		
	FX Series (Communication expansion board)	FX3U-ENET-L	FX-485ADP/485BD/232BD		
	Q Series (Port built into CPU)		Q00, Q00J, Q01, Q02, Q02H, Q06H, Q12H, Q25H		
Mitsubishi	QnU Series (Port built into CPU)	Q03UDE, Q04UDEH, Q06UDEH, Q10UDEH, Q13UDEH, Q20UDEH, Q26UDEH, Q50UDEH, Q100UDEH	Q00UCPU, Q01UCPU, Q02UCPU, Q03UD, Q04UDH, Q06UDH		
	QnUDV Series (Port built into CPU)	Q26UDV			
	Q Series (Communication Unit)	QJ71E71-100	QJ71C24/-R2 QJ71C24N/-R2/-R4		
	L Series (Port built into CPU)	L02CPU/-P, L06CPU/-P, L26CPU/-P/-BT/-PBT			
	L Series (Communication Unit)	LJ71E71-100	LJ71C24/-R2		
KEYENCE	KV Series (Port built into CPU)	KV-5000	KV-3000		
Panasonic	FP Series		FP, FP0, FP1, FP2, FP3, FP2SH, FP10S/SH, FP-M, FP-e, FP-X		
	S7-200 Series	CP243-1, CP243-1 IT, SMART CPU CR40, SMART CPU SR20	CPU212/214/215/216 CPU221/222/224/226		
Siemens	S7-300/400 Series	CP343-1, CP343-1 IT, CPU315-2 PN/DP, CPU317-2 PN/DP, CPU319-3 PN/DP	CPU312/313/314/315/316/318 CPU412/413/414/416/417		
	S7-1200 Series	CPU1211C, CPU1214C			
Allen-Bradley (Rockwell)	SLC500/MicroLogix Series	MicroLogix 1100/1400 (Built-in Ethernet port), MicroLogix 1000/1200/ 1400/1500 (1761-NET-ENI Unit)	MicroLogix1000/1200/1400/1500 SLC 5		
	CompactLogix/ControlLogix Series		1756-L61/63 1769-L20/30/31/32E/35E		
Schneider	TSX-Micro/Premium/Nano Series		TSX 37/P57/07		
	Twido Series		TWD LCAA/LMDA		
	Series 90-30		IC693CPU/CSE		
GE Fanuc	VersaMax/ VersaMax Micro & Nano Series		CPU001/002/005/E05 IC200UAL/UDD/UDR/UAA/UAR		
Delta	DVP Series		DVP-DES/EX/SS DVP-DSA/SX/SC DVP-DEH/EH2/SV		
IG (IS)	Master-K Series		K120s, K200s		
LG (LS)	XGT Series		XGB		
Modbus	Modbus	Modbus TCP Slave	Modbus ASCII Modbus RTU Modbus RTU Slave Modbus RTU Extend OMRON:Temperature Controller etc.		

Note: 1. OMRON does not guarantee the normal operation of all PLCs in each series. The NB series can be connected to temperature controllers, inverters, and other devices. For details, refer to the *NB Series Host Connection Manual* (Cat.No V108).
2. Including models whose production were discontinued.

# Providing components for designing screens with NB-series

Omron provides components for designing the screens with NB-series.

Use of components allows customers to easily and neatly create the HMI screens.

## **Cool objects**

Sample screens, bit switches, and bit lamps are provided in three types such as

"Pop", "Natural", and "Metal".Buttons can be used for labels,

or as ON/OFF buttons in combination with gray buttons.

You can choose components that meet your application from objects in different sizes and colors.



Metal

MEMO

# **Terms and Conditions Agreement**

#### Read and understand this catalog.

Please read and understand this catalog before purchasing the products. Please consult your OMRON representative if you have any questions or comments.

#### Warranties.

- (a) Exclusive Warranty. Omron's exclusive warranty is that the Products will be free from defects in materials and workmanship for a period of twelve months from the date of sale by Omron (or such other period expressed in writing by Omron). Omron disclaims all other warranties, express or implied.
- (b) Limitations. OMRON MAKES NO WARRANTY OR REPRESENTATION, EXPRESS OR IMPLIED, ABOUT NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE OF THE PRODUCTS. BUYER ACKNOWLEDGES THAT IT ALONE HAS DETERMINED THAT THE PRODUCTS WILL SUITABLY MEET THE REQUIREMENTS OF THEIR INTENDED USE.

Omron further disclaims all warranties and responsibility of any type for claims or expenses based on infringement by the Products or otherwise of any intellectual property right. (c) Buyer Remedy. Omron's sole obligation hereunder shall be, at Omron's election, to (i) replace (in the form originally shipped with Buyer responsible for labor charges for removal or replacement thereof) the non-complying Product, (ii) repair the non-complying Product, or (iii) repay or credit Buyer an amount equal to the purchase price of the non-complying Product; provided that in no event shall Omron be responsible for warranty, repair, indemnity or any other claims or expenses regarding the Products unless Omron's analysis confirms that the Products were properly handled, stored, installed and maintained and not subject to contamination, abuse, misuse or inappropriate modification. Return of any Products by Buyer must be approved in writing by Omron before shipment. Omron Companies shall not be liable for the suitability or unsuitability or the results from the use of Products in combination with any electrical or electronic components, circuits, system assemblies or any other materials or substances or environments. Any advice, recommendations or information given orally or in writing, are not to be construed as an amendment or addition to the above warranty.

See http://www.omron.com/global/ or contact your Omron representative for published information.

#### Limitation on Liability; Etc.

OMRON COMPANIES SHALL NOT BE LIABLE FOR SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, LOSS OF PROFITS OR PRODUCTION OR COMMERCIAL LOSS IN ANY WAY CONNECTED WITH THE PRODUCTS, WHETHER SUCH CLAIM IS BASED IN CONTRACT, WARRANTY, NEGLIGENCE OR STRICT LIABILITY.

Further, in no event shall liability of Omron Companies exceed the individual price of the Product on which liability is asserted.

#### Suitability of Use.

Omron Companies shall not be responsible for conformity with any standards, codes or regulations which apply to the combination of the Product in the Buyer's application or use of the Product. At Buyer's request, Omron will provide applicable third party certification documents identifying ratings and limitations of use which apply to the Product. This information by itself is not sufficient for a complete determination of the suitability of the Product in combination with the end product, machine, system, or other application or use. Buyer shall be solely responsible for determining appropriateness of the particular Product with respect to Buyer's application, product or system. Buyer shall take application responsibility in all cases.

NEVER USE THE PRODUCT FOR AN APPLICATION INVOLVING SERIOUS RISK TO LIFE OR PROPERTY OR IN LARGE QUANTITIES WITHOUT ENSURING THAT THE SYSTEM AS A WHOLE HAS BEEN DESIGNED TO ADDRESS THE RISKS, AND THAT THE OMRON PRODUCT(S) IS PROPERLY RATED AND INSTALLED FOR THE INTENDED USE WITHIN THE OVERALL EQUIPMENT OR SYSTEM.

#### Programmable Products.

Omron Companies shall not be responsible for the user's programming of a programmable Product, or any consequence thereof.

#### Performance Data.

Data presented in Omron Company websites, catalogs and other materials is provided as a guide for the user in determining suitability and does not constitute a warranty. It may represent the result of Omron's test conditions, and the user must correlate it to actual application requirements. Actual performance is subject to the Omron's Warranty and Limitations of Liability.

#### Change in Specifications.

Product specifications and accessories may be changed at any time based on improvements and other reasons. It is our practice to change part numbers when published ratings or features are changed, or when significant construction changes are made. However, some specifications of the Product may be changed without any notice. When in doubt, special part numbers may be assigned to fix or establish key specifications for your application. Please consult with your Omron's representative at any time to confirm actual specifications of purchased Product.

#### Errors and Omissions.

Information presented by Omron Companies has been checked and is believed to be accurate; however, no responsibility is assumed for clerical, typographical or proofreading errors or omissions.

Note: Do not use this document to operate the Unit.

#### OMRON Corporation Industrial Automation Company

#### Kyoto, JAPAN

#### Contact: www.ia.omron.com

Regional Headquarters OMRON EUROPE B.V. Wegalaan 67-69, 2132 JD Hoofddorp The Netherlands Tel: (31)2356-81-300/Fax: (31)2356-81-388

OMRON ASIA PACIFIC PTE. LTD. No. 438A Alexandra Road # 05-05/08 (Lobby 2), Alexandra Technopark, Singapore 119967 Tel: (65) 6835-3011/Fax: (65) 6835-2711 OMRON ELECTRONICS LLC 2895 Greenspoint Parkway, Suite 200 Hoffman Estates, IL 60169 U.S.A. Tel: (1) 847-843-7900/Fax: (1) 847-843-7787

OMRON (CHINA) CO., LTD. Room 2211, Bank of China Tower, 200 Yin Cheng Zhong Road, PuDong New Area, Shanghai, 200120, China Tel: (86) 21-5037-2222/Fax: (86) 21-5037-2200 Authorized Distributor:

© OMRON Corporation 2011-2018 All Rights Reserved. In the interest of product improvement, specifications are subject to change without notice. CSM\_11\_3\_1119

Cat. No. V412-E1-10

1018(1211)